If you are using a printed copy of this procedure, and not the on-screen version, then you <u>MUST</u> make sure the dates at the bottom of the printed copy and the on-screen version match.

The on-screen version of the Collider-Accelerator Department Procedure is the Official Version.

Hard copies of all signed, official, C-A Operating Procedures are kept on file in the C-A ESHQ

Training Office, Bldg. 911A.

C-A OPERATIONS PROCEDURES MANUAL

ATTACHMENT

4.56.m SEB "A2" Primary Cave Sweep Checklist

4.	.56		
	<u>Hand Pro</u>	cessed Changes	
<u>0.</u>	<u>Date</u>	Page Nos.	<u>Initials</u>
_			

P. Ingrassia

SEB "A2" PRIMARY CAVE SWEEP CHECKLIST

(Team Lead	der)(Operator 2)		
Time:	Date:		
	Warning: If any personnel are encountered during the sweep, then they will remain with the sweeper or the sweep shall be aborted. If the sweep is aborted then the person(s) must be escorted out of the cave by unlocking and opening the "A2" Primary Cave Gate.		
rerequisites			
BNL keys C-A-OPM Controlled	ators to perform the sweep , Nos. 14, H693 I-ATT 4.56.m SEB "A2" PRIMARY CAVE SWEEP CHECKLIST (1 page) I Access enabled by simultaneous operation of H693 key switch & MCR_2-1S2 push-button rming (chirping) Self Reading Dosimeter (SRD)		
<u> </u>	Both Operators enter "A2" Primary Gate (BNL 14 key).		
	Warning: The gate cannot be locked behind you.		
2. 3. 4. 5.	Operator 2 stands static watch in labyrinth by standing next to A2D5. Team Leader sweeps to the right, (upstream) through the labyrinth and into the cave to A2Q7, where to A2 cave ends. Team Leader sweeps downstream (beam left in A2) and searches under the A2 magnets. Team Leader searches under A2Q9 and the Decay tank, imbedded in the shielding, before re-entering the searches under A2Q9 and the Decay tank, imbedded in the shielding.		
6.	labyrinth. Team Leader sweeps downstream through the labyrinth, turns right and verifies that the mesh barrier und A2D5 is in place.		
7. 8. 9.	Both Operators sweep through the A2 Primary Gate. Lock and reset (BNL 14 key) the "A2" Primary Gate. The following lights will be lit (check them off) on the gate reset station when the gate is reset:		
	 Door Switch Bolt Switch Emergency Switch Reset Redundant Door Switch 		
10.	Verify with MCR that A2 Primary Gate is rest by viewing the indicator at MCR_2-1S9.		

11.

File the checklists in the Completed Sweep Checklist Binder.